



**WACKER
NEUSON**
all it takes!

BOB14

5100069473

[Home](#) >> [Catalog](#) >> [Products](#) >> [Power supply](#) >> [Power Storage](#) >> [Batteries & Charger](#) >> **BOB14**

BOB14

Material number 5100069473

Lithium-ion battery with 1425 Wh energy content, for longer running times



Product details

Highlights

- Battery One battery system
- Long running time with one battery charge
- Wide range of applications
- Systainer transport box
- Sturdy and durable
- Battery One app

Comes with

- Battery in Systainer® transport box

Technical specifications

BOB14

ELECTRICAL - OUTPUT DETAILS	Imperial	Metric
Nominal voltage	51,0 V	51,0 V
Kind of current (Output)	DC	DC

ELECTRICAL SYSTEM	Imperial	Metric
Load time 100% BOC13	140 min	140 min
Range APS2050e	11.464 ft2	1.065 m2
Range AP2560e	5.683 ft2	528 m2
Charge level indicator	yes	yes
Range AS68e	1.082,7 Foot	330 m
Load time 80% BOC13	105 min	105 min
Battery identifier	14INR19/66-8	14INR19/66-8
Load time 80% BOC7	200 min	200 min
Load time 100% BOC7	255 min	255 min
Range APS1030e	6.566 ft2	610 m2
Range AP1850e	9.494 ft2	882 m2
Range AP1840e	9.192 ft2	854 m2
Range AS30e	2.526,2 Foot	770 m
Range AS62e	1.230,3 Foot	375 m
Range AS50e	1.154,9 Foot	352 m
Installed energy	1.425,0 Wh	1.425,0 Wh
Range AS60e	1.023,6 Foot	312 m
Range APS1550e	10.333 ft2	960 m2
Range APS1135e	8.234 ft2	765 m2
Installed capacity	28,0 Ah	28,0 Ah
Range APS1340e	9.903 ft2	920 m2
Range ACBe	5,6 h	5,6 h
Type of battery	Li-Ion	Li-Ion

Breaker Switch On/Off	Yes	Yes
-----------------------	-----	-----

ENVIRONMENT DATA	Imperial	Metric
Operating temperature range	14 - 122 °F	-10 - 50 °C
Storage temperature range	-4 - 122 °F	-20 - 50 °C
Degree of protection	IP2X	IP2X
Temperature range charging	32,0 - 113,0 °F	0 - 45 °C

MECHANICAL DETAILS	Imperial	Metric
Length	11,7 "	296 mm
Height	12,7 "	322 mm
Width	15,6 "	396 mm
Weight	21,96 lb	9,96 kg

Please Note

This product availability can vary from country to country. It is possible that information / products may not be available in your country. More detailed information on engine power can be found in the operator's manual; the started power may vary due to specific operating conditions. Subject to alterations and errors expected. Applicable also to illustrations.
Copyright © 2024 Wacker Neuson SE